

PART 1 - GENERAL REQUIREMENTS

1-01 SCOPE OF WORK

WORK INCLUDED: Furnish all necessary labor, material, plant and equipment, including materials and equipment not specifically mentioned but necessary to complete the work in a neat, correct, and workmanlike manner, to include:

- 1) Complete branch circuit wiring system for equipment, and outlets.
- 2) Fire Alarm System, see Section 283100.

ALLOWANCE - DUCT DETECTOR: Include a separate lump sum cash allowance of \$20,000 in bid to replace existing duct mounted smoke detector assemblies determined to be faulty/inoperable during the fire alarm system testing. Replacement costs shall be based on unit pricing included with bid. At end of project credit owner with any amount not spent.

UNIT PRICES: Refer to "FIRE ALARM SYSTEM UNIT PRICING: on E001 for additional information.

1. UNIT PRICE #1: HVAC unit duct mounted smoke detector with control relay and keyed alarm/switch.
2. UNIT PRICE #2: Fire/Smoke Damper duct mounted smoke detector with control relay and keyed alarm/switch.
3. UNIT PRICE #3: Control relay for operation with existing duct mounted smoke detector and keyed alarm/switch.

SPECIAL NOTE: The provisions of the Instructions to Bidders, General Conditions, Supplementary General Conditions and all applicable requirements of Division 1 shall govern the work under this Division the same as if incorporated herein.

1-02 EQUIPMENT WIRING

VOLTAGE: The Electrical Contractor shall supply power to equipment at the voltage indicated on the electrical drawings. The Electrical Contractor and the other applicable trades will be held responsible for coordinating the equipment voltages, the control equipment wiring, and the location and type of disconnect required to comply with the equipment manufacturer's requirements, the National Electric Code, and applicable local building codes.

1-03 EXISTING CONDITIONS

The Contractor will be held responsible for having visited the site and having familiarized himself with the existing conditions prior to submitting his bid.

1-04 COORDINATION

OTHER TRADES: All work under this Section shall be coordinated with other trades to ensure proper location of outlets and equipment connections, and to minimize conflicts with structural members, duct work, piping, etc. Conflicts between equipment and/or material locations shall be corrected as directed by the Architect-Engineer at no additional cost to the Owner.

1-05 CODES AND PERMITS

Installation and materials shall be in accordance with the applicable versions of the National Electrical Code, the International Building Code, and all local codes. Apply and pay for all permits and fees required for this construction.

1-06 DRAWINGS

The drawings and specifications shall be considered as complementary, one to the other, so that materials and labor indicated, called for, or implied by either shall be furnished and installed as if required by both. Where a disagreement exists between the plans and specifications, the item or arrangements of better quality, greater quantity, or higher cost shall be included in the base bid. Any discrepancies between the drawings, specifications, and field conditions shall be resolved with the Engineer prior to commencing work. All agreements shall be verified in writing.

RECORD DRAWINGS: The Contractor shall maintain one set of clean blueprints for "RECORD" drawings. All changes, revisions, or modifications to the project shall be recorded daily on these drawings with **redline pencil**. Upon completion of the project, these redline drawings shall be turned over to the Engineer for preparation of final Record Drawings. All changes, revisions, or modifications on the redline drawings provided to the Engineer shall be noted in red or shall be highlighted in yellow. **Failure to comply with the above criteria may result in rejection of the Record Drawings by the Architect-Engineer.**

1-07 MAINTENANCE AND OPERATING MANUALS

The Contractor shall furnish the Owner two (2) complete maintenance and operating manuals for each piece of equipment and material furnished under this project. These manuals shall be bound in hard cover binders with tabs for each section item or piece of equipment. The manuals shall be furnished to the Engineer prior to the final observation, and final acceptance shall not be given until the Owner's maintenance personnel are instructed in maintenance and operation of all systems.

1-08 GUARANTEE

All materials and labor furnished under this Section of the specifications shall be guaranteed by the Contractor to be free from defects for a period of one year from the date of acceptance. The Contractor shall repair or replace any deficiencies reported in the guarantee period promptly after notification, without any additional compensation from the Owner. LED lamps are included in this warranty. Incandescent, fluorescent, & HID lamps are excluded from this warranty, except that all lamps shall be operational on the date of acceptance.

1-09 MATERIALS

UL LISTING: All materials shall be listed by Underwriter's Laboratories, or an approved equal testing laboratory, and shall bear the "UL" Label, where applicable.

SUBSTITUTIONS: Specific reference in the specifications to any article, device, product, material, fixture, form or type of construction, etc., by name, make or catalog number, with or without the words "or equal" shall be interpreted as establishing a standard of quality and shall not be construed as limiting competition and the Contractor in such cases may, at his option, use any article, device, product, material, fixture, form or type of construction, which in the judgment of the Architect-Engineer, expressed in writing prior to bidding as specified below, is equal to that herein named. **EXCEPTION:** All new fire alarm system equipment shall be compatible with existing EST equipment, no exceptions.

Requests to substitute materials or equipment considered by the Contractor as equal to those specified shall be submitted for review to the Architect-Engineer ten (10) days before bids are taken. Requests shall be accompanied by samples, descriptive literature, and engineering information, as necessary to fully identify and appraise the product. No increase in the contract sum will be considered when requests are not accepted. If the item is found to be equal, the Architect-Engineer will issue an Addendum making it a part of the Contract Documents prior to bidding.

1-10 SUBMITTALS

Electrical shop drawings shall be submitted in one complete package containing all items required by this specification and all other Division 26-28 specifications. Partial shop drawing submittals may be rejected by the Architect-Engineer.

Exceptions: Fire Alarm System CAD drawings, Lighting Control System CAD drawings, and Allowed Light Fixtures may be submitted separately if additional time is needed to prepare these shop drawings.

Refer to Section 260510 - Electrical Submittals for additional information.

PART 2 - MATERIALS

2-01 GENERAL REQUIREMENTS

COORDINATION: Coordinate arrangement, mounting, and support of electrical equipment to allow maximum possible headroom (unless specific mounting heights that reduce headroom are indicated), to provide for ease of disconnecting the equipment with minimum interference to other installations, to allow right of way for piping and conduit installed at required slope, and so connecting raceways, cables, wireways, cable trays, and busways will be clear of obstructions and of the working and access space of other equipment.

2-02 GROUNDING

INSULATED CONDUCTORS: Copper wire or cable insulated for 600 V unless otherwise required by applicable Code or authorities having jurisdiction.

BARE COPPER CONDUCTORS:

- 1) Solid Conductors: ASTM B3.
- 2) Stranded Conductors: ASTM B8.
- 3) Tinned Conductors: ASTM B33.
- 4) Bonding Cable: 28 kcmil, 14 strands of No. 17 AWG conductor, 1/4 inch in diameter.
- 5) Bonding Conductor: No. 4 or No. 6 AWG, stranded conductor.
- 6) Bonding Jumper: Copper tape, braided conductors, terminated with copper ferrules; 1-5/8 inches wide and 1/16 inch thick.
- 7) Tinned Bonding Jumper: Tinned-copper tape, braided conductors, terminated with copper ferrules; 1-5/8 inches wide and 1/16 inch thick.

2-03 RACEWAYS AND FITTINGS

GALVANIZED RIGID CONDUIT (GRC): UL 6 and ANSI C80.1 with full weight screwed fittings. Bushings shall be malleable iron. Bushings 1 1/4" and larger shall have insulated throat and grounding lug.

INTERMEDIATE GRADE METALLIC CONDUIT (IMC): UL 1242 and ANSI C80.6, galvanized, with full weight screwed fittings. Bushings shall be as specified above.

ELECTRICAL METALLIC TUBING (EMT): UL 797 and ANSI C80.3 with steel compression or set-screw type fittings. Die-cast fittings are not acceptable. Fittings 1 1/4" and larger shall have nylon

insulated throat. Indented or drive-on fittings are not acceptable. Conduit used for Fire Alarm System wiring shall be red, similar to Allied Fire Alarm EMT.

FLEXIBLE STEEL CONDUIT (GREENFIELD): UL 1. Fittings shall be steel.

LIQUIDTIGHT FLEXIBLE STEEL CONDUIT (SEALTITE): UL 360. Fittings shall be steel compression type.

PLASTIC CONDUIT (PVC): Schedule 40 polyvinylchloride. NEMA Standard TC-2 and TC-3 and UL Standards. Conduit, solvent, and fittings shall all be supplied by the same manufacturer. PVC is not permitted above grade.

SURFACE METAL RACEWAY (INDOOR): Wiremold V700 ivory surface metal raceway, or acceptable equivalent. Straps, boxes, elbows, etc. shall all be supplied by the same manufacturer. Total cross-sectional area shall be a minimum of 0.25 square inches.

2-04 WIRE AND CABLE

UL STANDARDS: UL 44 and UL 83.

CONDUCTOR: Copper, soft drawn, per ASTM B3 and comply with NEMA WC 70. Sizes No. 12 and 10 shall be solid conductor. Sizes No. 8 and larger shall have Class B concentric stranding per ASTM B8. Stranded conductors may not be used on No. 12 and No. 10 circuits.

INSULATION: 600 Volt, 90°C rated, comply with NEMA WC 70. Type THHN-THWN-MTW, unless noted otherwise.

SPLICING MATERIALS:

No. 10 and smaller: Acceptable wire nuts or insulated crimped splice caps.
No. 8 and larger: Bronze or copper split bolts, or tinned compression connectors.
(Polaris insulated splice blocks may not be used on this project).

Insulation shall be Scotch No. 23 rubber tape and Scotch No. 33 plastic tape, or approved equivalent method.

Power feeders shall not be spliced.

2-05 BOXES AND WIREWAYS

OUTLET BOXES: Galvanized sheet steel per UL 514. "Through-wall" boxes SHALL NOT BE USED. Back-to-back mounting of boxes is not permitted. All outlet boxes 4"x4" or smaller located on opposite sides of a rated wall shall have a minimum of 24" horizontal spacing or shall be protected with listed putty pads. All outlet boxes larger than 4"x4" (communications outlets, etc.) located in rated walls shall be protected with listed putty pads.

Box sizes shall be as follows:

- 1) Wall Receptacle Outlets: 4" square by 2 1/8" deep with plaster ring as required.
- 2) Wall Computer, Communications and TV Outlets (up to 1" conduit): 4" square by 2 1/8" deep with one gang plaster ring. Provide box with 1" conduit knockouts.
- 3) Wall Computer, Communications and TV Outlets (1 1/4" conduit):: 4 11/16" square by 2 1/8" deep with one gang plaster ring. Provide box with 1 1/4" conduit knockouts.
- 4) Ceiling outlets: 4" square or octagonal by 1 1/2" or 2 1/8" deep with stud or ears where required for fixture support.

- 5) Indoor Surface Mounted Outlets: Wiremold V5744S-2 surface metal box unless noted otherwise on the drawings (steel boxes and EMT conduit may be used in equipment rooms, janitor's closets, storage rooms).
- 6) Exposed Outlets: Malleable iron or heavy duty cast aluminum with threaded hubs, Type FS, FD, or GS. Manufactured by Crouse Hinds, Appleton, Killark, or approved equal. Die cast boxes are not acceptable.

SUPPORT FOR RECESSED BOXES IN MASONRY WALLS: Saw-cut opening for box in center of cell of masonry block, and install box flush with surface of wall.

SUPPORT FOR RECESSED BOXES IN STUD WALLS: Support boxes from more than one side by spanning two framing members or mounting on brackets specifically designed for the purpose. Box brackets reliant on support legs pressed against back of opposing wall are not acceptable.

WIREWAYS, PULL BOXES AND JUNCTION BOXES: UL 50. NEMA 250, Type 12 unless otherwise indicated. Code gage galvanized sheet steel, aluminum, or steel primed and painted after fabrication. Manufactured by Square D, Austin Berryhill, Hoffman Engineering, B-Line Systems, or approved equal. Wireways shall have hinged covers.

2-06 NAMEPLATES

NAMEPLATE: Provide engraved 3-ply laminated plastic nameplates for each fire alarm cabinet, NAC panel, amplifier cabinet, etc. Attach to equipment cover using metal screws, rivets, or industrial epoxy cement. Manufacturer's sticky-back adhesive is not acceptable. Use 1/4" white letters on red field.

PART 3 - EXECUTION

3-01 GENERAL REQUIREMENTS

WORKMANSHIP: All work shall be installed in a neat and orderly manner. Devices, cabinets, covers, fixtures, exposed raceways, etc., shall be aligned parallel or perpendicular to the building walls, ceiling, and floor. Wiring in panelboards and cabinets shall be neatly looped and laced, and not wadded. The Owner reserves the right to require repair or replacement of defective workmanship and material without additional compensation to the Contractor.

SUPPORTS: Conduits, boxes, cabinets, enclosures, etc., shall be securely supported by structural members or structural walls at intervals required by the NEC or as recommended by the manufacturer. Plaster, gypsum board, acoustical tile, and other ceiling and wall finish materials shall not be used for support.

Recessed light fixtures and recessed ceiling speakers shall be independently supported by two (2) or four (4) #12 steel hanger wires. Hanger wires shall be hung within 10 degrees of plumb, and shall be securely tied to structural members such as steel joists or beams, or to steel angles or tubing which bridge structural members. In addition to hanger wires, recessed light fixtures shall be securely fastened to the ceiling framing member per the requirements of NEC 410.36(B). All wiring located above fire rated assemblies must comply with the requirements of NEC 300.11(A)(1).

CUTTING, PATCHING, AND PAINTING: The Contractor shall perform all boring, drilling, and cutting of walls, ceilings, and floors as required to install and support his raceways and equipment. Provide rough patching to seal penetrations through walls, ceilings, and floors. Finish patching and painting will be performed by the Contractor.

FIRE WALL PENETRATIONS: Penetrations through fire rated walls and floors shall be sealed to maintain the integrity of the fire rating. Raceways through penetrations shall be in metal raceways. Penetration openings shall be sealed after the installation of the raceway with UL-49 listed fire retardant material in accordance with Section 078413. Through penetrations of conduits and cables of fire resistance rated walls must comply with Section 714.3.1 of the IBC. Through penetrations of fire resistance ceiling assemblies must comply with section 714.4.1.1 of the IBC.

ROOF PENETRATIONS: Do not penetrate roof or flashing unless permitted, in writing, by the Architect-Engineer.

3-02 GROUNDING

CODE: Entire system shall be grounded and bonded in accordance with the requirements of Article 250 of the National Electrical Code. Comply with UL 467 for grounding and bonding materials and equipment. Comply with IEEE C2 grounding requirements.

GROUNDING CONDUCTORS: Route along shortest and straightest paths possible, unless otherwise indicated or required by Code. Avoid obstructing access or placing conductors where they may be subjected to strain, impact, or damage. Install solid conductor for No. 8 AWG and smaller, and stranded conductors for No. 6 AWG and larger, unless otherwise indicated.

FEEDERS AND BRANCH CIRCUITS: Each feeder raceway shall be bonded to every cabinet, pull box, etc., to which it is connected by grounding bushings and bonding jumpers sized per NEC Table 250.122. Each branch circuit raceway must be connected to every cabinet, pull box, outlet box, etc., with double locknuts. Separate grounding conductors shall be installed on all feeders and on all lighting, receptacle and equipment branch circuits, whether indicated on the drawings or not. Size per NEC 250.122.

3-03 RACEWAYS

WIRING: All wiring shall be installed in raceways, unless noted. Raceways shall be run concealed, unless noted.

BRANCH CIRCUITS:

- 1) Branch circuits shall be run concealed where practical.
- 2) Branch circuits run concealed in walls or ceilings shall be run in EMT, GRC, or IMC.
- 3) Branch circuits run exposed to weather (wet or damp location) on exterior walls, canopies, ceilings, or on roofs shall be run in GRC or IMC with screwed fittings.
- 4) Branch circuits run exposed in dry, finished spaces shall be run in Wiremold surface metal raceway.
- 5) Branch circuits run exposed in interior damp locations, unfinished spaces (attics), and unoccupied spaces (storage room, equipment rooms, janitor's closet) may be run in EMT in lieu of Wiremold.
- 6) Branch circuits run underground shall be run in GRC, IMC, or Schedule 40 PVC plastic conduit.
- 7) All interior conduit homeruns to panelboards shall be run overhead in EMT, GRC, or IMC unless noted otherwise on the drawings.
- 8) Underground conduits shall be run 24" minimum below grade.
- 9) Metal conduits installed in contact with earth shall be painted with 2 coats Rustoleum paint or other acceptable preservative.
- 10) Where plastic conduits are indicated, transition from plastic to GRC or IMC below grade or slab and rise with GRC or IMC. PVC is not permitted above grade. EXCEPTIONS: 1) Plastic conduit may enter floor mounted switchboards, motor control centers, or other floor mounted enclosures. 2) Plastic conduit risers are acceptable where run concealed from underfloor conduit to receptacle or switch boxes in masonry walls.

COMMUNICATIONS CONDUIT:

- 1) All conduit for Communications Systems within the building shall be run above grade in walls and above ceiling in metal raceways. Conduit shall be run concealed in all areas not designated as a utility or electrical room, except surface mounted raceway may be used where devices are installed on existing walls. Communications conduit wiring may not be run underground or in slab unless specifically noted otherwise on the drawings.
- 2) Service-Entrance communications conduit and communications conduit run underground between buildings shall be run in Schedule 40 PVC encased in concrete with 2-inches minimum concrete encasement on all sides (Schedule 40 PVC is not required to be encased in conduit where run under the concrete floor slab). PVC is not permitted above grade.

FIRE ALARM SYSTEM CONDUIT:

- 1) All Fire Alarm System wiring within the building shall be run above grade in walls and above ceiling in metal raceways. Raceways shall be run concealed in all areas not designated as a utility or electrical room, except surface mounted raceway may be used where devices are installed on existing walls. Fire alarm wiring may not be run underground or in slab unless specifically noted otherwise on the drawings.
- 2) Conduit within the building used for Fire Alarm System wiring shall be red, similar to Allied Fire Alarm EMT, except where noted otherwise on the drawings. EXCEPTION: Fire Alarm System raceway run exposed in finished spaces shall be Wiremold V700 or equivalent.
- 3) Fire Alarm System wiring run underground between buildings shall be run in Schedule 40 PVC encased in concrete with 2-inches minimum concrete encasement on all sides (Schedule 40 PVC is not required to be encased in conduit where run under the concrete floor slab). PVC is not permitted above grade.

FLEXIBLE CONDUITS: Recessed light fixtures located in accessible ceilings may be connected to an outlet box above the ceiling thru flexible conduit "whips". Run a separate ground wire in all conduit, including flexible fixture whips. DO NOT loop flexible conduit from one fixture to another. Manufacturer-supplied Metal-clad cable fixture whips (#18 AWG) shall be permitted for light fixture whips provided they include a ground wire and do not exceed 6' in length.

Final connections to motors, motor driven equipment, transformers, and vibrating equipment shall be made thru flexible conduit, 36" maximum length. "Sealtite" flexible metal conduit shall be installed outdoors, in equipment rooms, and in wet locations.

PULL WIRES: Raceways for wiring by others or for future shall contain a No. 14 galvanized steel pull wire or equivalent plastic cord with 200 lb. tensile strength.

INSTALLATION: Ream raceways, butt ends into couplings, 3 quarter bends per run maximum, plug raceways until wiring is pulled in place. Exposed conduits shall be run parallel and perpendicular to walls, floor, and ceiling. Multiple conduit runs shall be racked using Unistrut or Kindorf channels and pipe clamps. Install conduits in concrete slabs between the top and bottom layers of reinforcing steel. Maximum size of conduits in slabs is 1 inch. Crossing of conduits in slabs shall be avoided, if possible.

PULL BOXES: Maximum length between pull points shall be 200 ft. for pulls with two 90 degree bends, and 100 ft for pulls with three 90 degree bends. Furnish and install pullboxes, junction boxes, handholes, or conduit bodies where bends or pulling lengths exceed these specifications.

EXPANSION JOINTS: Furnish and install expansion joints where conduit crosses building expansion joints and for straight runs exceeding 100 ft. in length.

PLASTIC CONDUIT: Do not damage conduit while making field bends and offsets, cutting and joining conduit. Use GRC elbows where length between pulls exceeds 100 ft. Clean conduit prior to applying solvent. Ensure that conduit extends fully into coupling or fitting when making joints.

MINIMUM SIZE: Home runs to panelboards shall be 3/4" minimum, otherwise raceways shall be 1/2" minimum, except that flexible conduit shall be 3/8" minimum.

FIRESTOPPING: Apply firestopping to electrical penetrations of fire-rated floor and wall assemblies to restore original fire-resistance rating of assembly. Firestopping materials and installation requirements are specified in Division 07 Section "Penetration Firestopping."

TEST AND INSPECTIONS: After installing conductors and cables and before electrical circuitry has been energized, test service entrance and feeder conductors for compliance with requirements. Perform each visual and mechanical inspection and electrical test stated in NETA Acceptance Testing Specification. Certify compliance with test parameters.

3-04 WIRE AND CABLE

MINIMUM SIZE: No. 12 for power circuits, No. 16 for control circuits, unless noted. Where home run exceeds 75 ft. length on 120 volt circuits, use No. 10 minimum.

COLOR CODE: No. 12 and No. 10 shall have color-coded insulation. No. 8 and larger shall be marked at all terminals and joints with color-coded tape. Color code as follows:

<u>Voltage</u>	<u>Phase A</u>	<u>Phase B</u>	<u>Phase C</u>	<u>Neutral</u>	<u>Grounding</u>
240/120	Black	Orange	Blue	White	Green
208/120	Black	Red	Blue	White	Green
480/277	Brown	Orange	Yellow	Gray	Green

INSTALLATION: Ensure that raceway system is complete and that conductors will be free from moisture or physical damage prior to installing conductors. Install all conductors at the same time. Do not exceed cable manufacturer's recommended pulling tension for conductors. Where required, lubricate cables with Ideal Yellow 77, Burndy Slikon, or other acceptable cable lubricant. Do not use lubricants that are not acceptable to the Architect-Engineer.

SPLICING: Splices on Sizes No. 10 and smaller shall be made with wire nuts. Splices on Sizes No. 8 and larger shall be made with split bolt connectors, compression connectors, or solderless lugs. Splices shall be insulated with two or more layers of Scotch 23 rubber tape covered with two or more layers of Scotch 33 plastic tape, or acceptable equivalent method.

CONNECTIONS: Tighten electrical connectors and terminals according to manufacturer's published torque-tightening values. Absent published values, use those specified in IL 486A and UL 486B.

MULTIWIRE BRANCH CIRCUITS: Shared or common neutrals are not permitted on this project for multiwire branch circuits. The Contractor shall pull a separate neutral for all 120V & 277V circuits.

3-05 BOXES

WALL OUTLETS: Flush mounted, unless noted. Boxes shall be securely mounted to wall studs or be grouted in masonry. Boxes shall have single or multi-gang plaster rings, as required. "Through-wall" boxes SHALL NOT BE USED. Back-to-back mounting of boxes is not permitted. Boxes on opposite sides of a rated wall shall have a minimum of 24" horizontal spacing or shall be protected with listed putty pads. Locate boxes so that cover or plate will not span different building finishes.

RECESSED BOXES IN MASONRY WALLS: Saw-cut opening for box in center of cell of masonry block, and install box flush with surface of wall. Prepare block surfaces to provide a flat surface for a raintight connection between the box and cover plate or the supported equipment and box.

RECESSED BOXES IN STUD WALLS: Support boxes from more than one side by spanning two framing members or mounting on brackets specifically designed for the purpose.

CEILING OUTLETS: Flush mounted or concealed above ceiling. Boxes for fixture support shall have studs or ears as required and shall be securely supported by adjustable bar hangers or steel angle.

JUNCTION BOXES, PULL BOXES, AND WIREWAYS: Shall be sized and installed as indicated on the drawings or where required by NEC for pulling or splicing wiring. All junction boxes and pull boxes shall be accessible. Junction boxes and pull boxes shall not be located above inaccessible ceilings.

LOCATIONS: Verify counter heights and arrangement prior to setting boxes. The Owner reserves the right to move any outlet by as much as 10 ft. from its indicated location at no additional cost, provided the Contractor is notified prior to roughing in.

3-06 NAMEPLATES AND WARNING SIGNS

INSTALLATION: Verify identity of each item before installing identification products. Install identification materials and devices at locations for most convenient viewing without interference with operation and maintenance of equipment.

3-07 COMPLETION OF WORK

TESTS AND FINAL REVIEW: Upon completion of work, the entire system shall be completely operational and tested to conform with these specifications and drawings, and shall be reviewed by the Architect-Engineer. All defects in workmanship and material shall be immediately corrected without additional compensation to the Contractor.

The final review of the electrical installation by the Engineer cannot be provided until the following items have been submitted to the Engineer for review:

- 1) Letter from the Electrical Contractor on company letterhead indicating that the installation is complete and ready for a final review.
- 2) Signed and dated certificate indicating that the specified functional tests of the Fire Alarm System have been performed.

Failure to submit the above documentation prior to requesting the Engineer's Final Review of the project may result in delays in providing the final review. The Engineer assumes no liability for delays in the project resulting from failure to provide the proper documentation.

The system will not be considered complete until Record Documents are provided and training of facility personnel on the system operation is complete. This facet of the services to be provided by the Contractor is deemed very important to the satisfactory completion of the contract and the installation cannot be deemed complete until these services have been provided in accordance with the Contract Documents.

CLEAN UP: Upon completion of all installations and prior to final acceptance by the Owner, remove all debris from the site. Clean and touch up paint on fixture lenses and trims, cabinets, enclosures, cover plates, etc.

END OF SECTION 260500